





Learn more about  
this product




## Your Gateway to Efficient Connectivity

Kvaser Memorator Professional 5xHS is a five-channel, high-performance CAN bus interface and stand-alone data logger that allows users to monitor and collect data from up to five CAN channels using just one device. Configurable using Kvaser's Memorator Config Tool, this device is capable of running user-developed scripts, written in the Kvaser t programming language.

 **Warranty**  
2-Year warranty. See our general conditions and policies for details.

 **Support**  
Free support for all products by contacting [support@kvaser.com](mailto:support@kvaser.com)

 **EAN**  
73-30130-00778-9

## Major Features

- CAN FD capable.
- Automatically time-synchronises the data transmitted and received across all five buses.
- Kvaser MagiSync technology time-synchronises with other Kvaser interfaces connected to the same PC, resulting in a more accurate and easier multichannel data capture.
- A comprehensive user guide helps make t script development quick and easy.
- Log data to an expandable SD card slot. SD and SDHC memory card formats supported.
- LED lights alert user to device status, including signaling a full SD card or card error.
- Power derived from the USB connection, CAN or an in-built power supply.
- Log continuously, or create triggers based on messages, data signal values, error messages, external trigger's falling or rising edge, and I/O signals.
- Compatible with J1939, CANopen, NMEA 2000® and DeviceNet. Higher layer protocol translation handled by the user's application. For software support please see our Technical Associates products and our Software Download page ([www.kvaser.com](http://www.kvaser.com)).

## Support

Documentation, Kvaser CANlib SDK and drivers can be downloaded for free at [www.kvaser.com/downloads](http://www.kvaser.com/downloads).

Kvaser CANlib SDK is a free resource that includes everything you need to develop software for the Kvaser CAN interfaces. Includes full documentation and many program samples, written in C, C++, C#, Delphi, Visual Basic, Python and t programming language.

Kvaser CAN hardware is built around the same common software API. Applications developed using one device type will run without modification on other device types.

## Technical Data

<b>Bit Rate</b>	40-1000 kbp/s
<b>Buffers</b>	Auto RX Buffers, Auto TX Buffers, On Board Buffer
<b>Certificates</b>	CE, RoHS
<b>Channels</b>	5
<b>Connectors</b>	26-pin HD D-SUB
<b>Dimensions</b>	68 x 170 mm
<b>Error Frame Generation</b>	Yes
<b>Error Counters Reading</b>	Yes
<b>Galvanic Isolation</b>	Yes
<b>Interfaces</b>	USB
<b>Messages Per Second Receive</b>	20000 mps
<b>Messages Per Second Sending</b>	20000 mps
<b>Silent Mode</b>	Yes
<b>Sound</b>	No
<b>Temperature Range</b>	-40 °C to +85 °C
<b>Weight</b>	150 g