



## Kvaser T-Cannector v2

EAN: 73-30130-00776-5

Kvaser T-cannector v2 is a CAN bus hub with three female and one male D-SUB9 connectors. Offering an adjustable CAN termination resistor (120 Ohm, 60 Ohm, or unterminated) it provides an affordable and safe way of terminating the CAN circuit when using Kvaser interfaces on a development board, as well as powering interface devices without internal power, such as Kvaser's Blackbird and Memorator series.

## **Major Features**

- Acts as a CAN bus hub with 3 female and 1 male D-SUB9 connectors
- Each DSUB9 has screws to secure the connection to the Kvaser CAN interface
- Adjustable termination via easy-to-use switch
- 12V 1A power supply
- LED to indicate power on
- Voltage range of 12V-24V DC

Kvaser Aminogatan 25 A SE 431 53 Mölndal SWEDEN Kvaser Europe AB Telephone: +46 31 886344 Email: sales@kvaser.com https://www.kvaser.com/



**Kvaser T-cannector v2** is a CAN bus hub with three female and one male D-SUB9 connectors. Used typically in application development scenarios, this offers an adjustable CAN termination resistor (120 Ohm, 60 Ohm, or unterminated) that provides an affordable and safe way of terminating the CAN circuit, as well as powering devices that take their power from the USB connection or the CAN network to which they are attached, such as Kvaser's Blackbird and Memorator series. This device comes with a 12V power supply and EU, USA, UK and Chinese plugs.

This is a new version of an existing product that responds to user requests for more termination options. Notably our previous product came in two versions: with fixed termination of 120 Ohms and without. The Kvaser T-cannector v2 is extremely price-competitive, providing an external 12V 1A power source for Kvaser CAN interfaces and a safe, trustworthy means of circuit termination that protects customer's interface investment and will prevent short circuits from damaging their development boards.

Kvaser Aminogatan 25 A SE 431 53 Mölndal SWEDEN Kvaser Europe AB Telephone: +46 31 886344 Email: sales@kvaser.com https://www.kvaser.com/



TECHNICAL DATA - KVASER T-CANNECTOR V2	
CURRENT CONSUMPTION	Up to 3W
RUGGED	No
TIMESTAMP RESOLUTION (US)	N/A
DATABASE DBC SUPPORT	No
OPERATING TEMPERATURE RANGE (C)	-30.00 to 85.00
GALVANIC ISOLATION	N/A
PC INTERFACE	Cable
EMBEDDED SCRIPT	No
SOUND	No
IP CLASS	IP40
ON-BOARD TX BUFFER	N/A
MSGRATE TX MAX	N/A
ON-BOARD RX BUFFER	N/A
LENGTH (MM)	90
HEIGHT (MM)	29
STATUS	Active
PRODUCT GROUPS	Accessory
API, FREE	N/A
OPERATING SYSTEM	Win XP,Linux,Win 7,Win Vista,Win 10,Win 8
CAN FD	No
WEIGHT (G)	400.0
NETWORK CHANNEL(S)	4 x CAN HS
MAXIMUM BITRATE (KBPS)	N/A
ERROR COUNTERS READING	No
CERTIFICATIONS	CE,RoHS
CASING MATERIAL	N/A
WIDTH (MM)	55

TECHNICAL DATA - KVASER T-CANNECTOR V2

Kvaser

Aminogatan 25 A SE 431 53 Mölndal SWEDEN Kvaser Europe AB Telephone: +46 31 886344 Email: sales@kvaser.com https://www.kvaser.com/



MINIMUM BITRATE (KBPS)	N/A
PROMOTIONAL_TEXT	CAN bus hub with three female and one male D-SUB9 connectors, termination.
SILENT MODE	No
MSGRATE RX MAX	N/A
# OF CAN CHANNELS	4
API, LICENCED	None
ERROR FRAME DETECTION	N/A
ERROR FRAME GENERATION	No
CONNECTOR	DSUB 9
ON-BOARD BUFFER	N/A
CLOCK SYNC	N/A
CB BOARD	No
The information have in a subject to change without paties	

The information herein is subject to change without notice

Kvaser Aminogatan 25 A SE 431 53 Mölndal SWEDEN Kvaser Europe AB Telephone: +46 31 886344 Email: sales@kvaser.com https://www.kvaser.com/